

The Unitronics® EX-D16A3-RO8 is an XL I/O expansion module for use in conjunction with specific Unitronics controllers. XL modules comprise enhanced I/O configurations and detachable I/O connectors. In addition, this module comprises a built-in adapter for communicating with the PLC and providing power to the other expansion modules in the system.

This module provides:

- 16 digital inputs, includes 2 HSC
- 3 analog inputs
- 8 relay outputs

For additional information and wiring diagrams, visit the Technical Library at [www.unitronics.com](http://www.unitronics.com).

### Technical Specifications

#### General

I/O module capacity	Up to 7 I/O expansion modules can be connected to this module. This number may vary according to the modules used.
Status indicators	
RUN: Green LED	<ul style="list-style-type: none"><li>▪ Lights when a communication link is established between the module and the PLC</li><li>▪ Blinks when the communication link fails</li></ul>
PWR: Green LED	<ul style="list-style-type: none"><li>▪ Lights when power is supplied</li></ul>

#### Power Supply

Input voltage	24VDC
Permissible range	20.4 to 28.8VDC, ripple < 10%
Maximum current consumption	90mA @ 24VDC – EX-D16A3-RO8 alone 220mA @ 24VDC – maximum load on the 5VDC supply when the EX-D16A3-RO8 powers seven additional I/O expansion modules
Current for additional modules	500mA maximum from 5VDC, see note 1

#### Notes:

1. For example, 2 IO-DI8-TO8 modules consume a maximum of 140mA of the adapter's 5VDC supply.

#### Digital Inputs

Number of inputs	16 (in a single group)
Input mode	pnp (positive logic) or npn (negative logic) – configurable by hard-wiring
Galvanic isolation	None
Status indicators	
IN: Green LEDs	<ul style="list-style-type: none"><li>▪ One green LED for each input: Lights when the input is active, see note 2</li></ul>
Nominal input voltage	24VDC
Input voltage	
pnp (positive logic)	0–5VDC for logic state 0 17–28.8VDC for logic state 1
npn (negative logic)	17–28.8VDC for logic state 0 0–5VDC for logic state 1
Input current	3.7mA @ 24VDC
Input impedance	6.5kΩ
Response time	10ms typical
High-speed inputs	The specifications in this section apply when inputs are configured as high-speed counters or frequency measurers. If they are configured as general purpose digital inputs, the specification is as above. See notes 3, 4, and 5.
Resolution	16-bit or 32-bit, depending on the PLC
Frequency	30kHz maximum (at 24VDC ±10%)
Minimum pulse width	14μs

#### Notes:

2. If the input is active but there is no communication with the PLC (RUN blinks), the status LED does not light.
3. Inputs 36 and 38 can function either as high-speed counters, frequency measurers, or general purpose digital inputs.
4. Inputs 37 and 39 can function either as counter reset inputs or general purpose digital inputs. In both cases, the specifications of these inputs are those of a general purpose digital input.
5. If input 36 or 38 is set as a high-speed counter and no reset input is configured, input 37 or 39 functions as a general purpose digital input.

**Analog Inputs**

Number of inputs	3
Input type	0–20mA or 4–20mA
Input impedance	191Ω
Maximum input rating	28mA, 5.3VDC
Galvanic isolation	None
Cable type	Shielded twisted-pair
Conversion method	Successive approximation
Resolution (0-20mA)	10-bit (1024 units)
Resolution (4-20mA)	204 to 1023 (820 units)
Conversion time	Each configured input is sampled once per 1.67ms. For example, if 3 inputs are configured, it takes $3 \times 1.67 = 5\text{ms}$ to sample all the analog inputs. See note 6.
Accuracy	±0.9% of full scale
Status indication	In software: If a specific input value is 1024, a single analog input deviates above the permissible range. If all the input values are 1024, either all the inputs deviate above the permissible range or the RG signal is not connected.

**Notes:**

6. The conversion time does not include communication time with the PLC and PLC scan time.

**Digital Outputs**

Number of outputs	8 relays
Output type	SPST-NO (Form A)
Isolation	By relay
Status Indicators	
OUT: Red LEDs	▪ One red LED for each output: Lights when the corresponding output is active
Type of relay	Tyco PCN-124D3MHz or compatible
Maximum output current	3A per output (resistive load) 8A total (resistive load), see note 7
Rated voltage	250VAC / 30VDC
Minimum load	1mA, 5VDC
Life expectancy	100k operations at maximum load
Response time	10ms (typical)
Contact protection	External precautions required (see <i>Increasing Contact Life Span</i> in the Installation Guide)
Output power supply	
Nominal operating voltage	24VDC
Operating voltage	20.4 to 28.8VDC
Maximum current consumption	40mA @ 24VDC

**Notes:**

7. Outputs 0–7 share the common signal C0.

**Dimensions**

Size (W x H x D)	80 x 135 x 60mm (3.15 x 5.31 x 2.36"). For exact dimensions, refer to the product installation guide.
Weight (approximate)	360g (12.7oz)

**Environmental**

Operating temperature	0° to 50°C (32° to 122°F)
Storage temperature	–20° to 60°C (–4° to 140°F)
Relative Humidity (RH)	10% to 95% (non-condensing)
Mounting	Snap-mounted on 35mm DIN-rail (IP20/NEMA1)

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the foregoing from the market. All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information. The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R<sup>®</sup>G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.